



UT-501 RS-232/RS-485/RS-422

UT-501 RS-232C
RS-422 RS-485 RS-232
RS-422 RS-485
2500Vrms
RS-422/RS-485 TVS
/TRANSIENT VOLTAGE SUPPRESSOR)
TVS TVS

LIGHTNING) 和ESD 600W的
RS-422/RS-485 RS-232
DB9 RS-232C
RS-422、RS-485
I/O
/ RTS、DTR fi 跳
/RS-422) (RS-485)
RS-232的
UT-501
32 RS-422 RS-485 300-115.2Kbps
RS-232 RS-422 RS-232 RS-485

1 EIA/TIA RS-232C RS-485/RS-422
2 RS-232 DB9 RS-422/
RS-485
3 RS-232 +/-15KV ESD RS-422
RS-485 600W
4 2500Vrms 500DC
5
6 PWR
TXD RXD
7
8 115.2Kbps 300m
38.4Kbps 600m
9600bps 1.2Km
9 117mm×80mm×25mm
10 -40 85 5% 95%
11 0-1200 115200bps-9600bps

RS-232C

DB9 / (PIN)	RS-232C
1	
2	SIN (RXD)
3	SOUT (TXD)
4	DTR
5	GND
6	DSR
7	RTS
8	CTS
9	RI

RS-485/RS-422

PIN		RS-422	RS-485
1	T/R+	(A+)	RS-485 (A+)
2	T/R-	(B-)	RS-485 (B-)
3	RXD+	(A+)	
4	RXD-	(B-)	
5	GND		
6	N/C		
7	N/C		
8	N/C		
9	VCC/)		
10	GND		

UT-501

RS-232
DB9
RS-485 RS-422
T/R+/T/R-
+/ Ĵ RXD+/RXD- +/ Ĵ GND
T/R+ T/R-
T/R+, T/R-, RXD+, RXD-

UT-501

1 /
2 /
3 /
4 /

/ 120 1/4W)

RS-232 RS-422

1 RS-422 /



